



Electronic transformers

ET-E 10W LED 220V-240V

A high frequency electronic transformer for operation with 12V halogen lamps. It is fully IEC compliant with unique compact size and light weight

Warnings and Safety

Transformer is not suitable for DC operation

Product data

General information	
Type version	-
Lamp type	-
Automatic restart	Yes
Operating and electrical	
Input Voltage	220 to 240 V
Input frequency	50 to 60 Hz
Power factor 100% load (nom.)	0.94
Mains voltage performance (AC)	202254V
Mains voltage safety (AC)	198264V
Inrush current width	0.10 ms
Power losses (nom.)	1 W
Inrush current peak (max.)	15 A
Output voltage	- V
Wiring	
Cable capacity wires device to lamp (max.)	120 nF
Cable length from device to lamp	1.5 m


Wire strip length	8.0-9.0 mm
System characteristics	
Rated ballast-lamp power	10 W
Temperature	
T-ambient (max.)	50 °C
T-ambient (min.)	-20 °C
T storage (max.)	50 °C
T storage (min.)	-40 °C
T-Case maximum (max.)	65 °C
Approval and application	
Humming and noise level	< 30 dB(A)
Product data	
Full product code	697013372907600
Order product name	ET-E 10 220-240V
EAN/UPC – product	6970133729076
Order code	72907600

Electronic transformers

SAP numerator - quantity per pack	1
Numerator – packs per outer box	48
SAP material	913710032179

Net Weight (Piece)	0.040 kg

Dimensional drawing



ET-E 10 220-240V



© 2022 Signify Holding All rights reserved. Signify does not give any representation or warranty as to the accuracy or completeness of the information included herein and shall not be liable for any action in reliance thereon. The information presented in this document is not intended as any commercial offer and does not form part of any quotation or contract, unless otherwise agreed by Signify. Philips and the Philips Shield Emblem are registered trademarks of Koninklijke Philips N.V.

 Product
 D1
 C1
 A1
 B1

 ET-E 10 220-240V
 4.4 mm
 24.5 mm
 76.0 mm
 38.0 mm